

## DIMAVERY GA-40R Electric Guitar Amp 40W

40 W guitar amplifier with digital reverb

Art. No.: 26360140

GTIN: 4026397201468



### Features:

- Guitar input high/low with gain control
- Overdrive function, switchable
- Reverb controls for length and depth
- Output for signal processing with further devices
- Rugged wooden housing with synthetic leather coating, plastic corners, carrying handle and rubber feet

### Logistic

EAN / GTIN: 4026397201468

Weight: 10,75 kg

Length: 0.51 m

Width: 0.27 m

Height: 0.41 m

### Technical specifications:

Power supply:	230 V AC, 50 Hz
Power consumption:	85.00 W
Output power:	40 W RMS
Power connection:	Fixed power supply cord with safety plug
Frequency range:	20 - 15000 Hz
S/N ratio:	>70 dB
Control elements:	Level control
Connections:	Input: 2 x 6.3 mm plug (unbal.) Output: headphones via 1 x 6.3 mm jack socket (stereo) mounting version Output: line via 1 x 6.3 mm jack socket (stereo) mounting version

Equalizer:	Master: 3-band tone control
Input sensitivity:	20 mV
Speaker:	1 x woofer 6" 1 x woofer 8"
Type of speaker:	Guitar speaker
Color:	Black
Dimensions:	Width: 49 cm Depth: 24.5 cm Height: 38 cm
Weight:	10.00 kg

### **Scope of delivery:**

---

1 x amplifier  
1 x user manual