eurolite®

EUROLITE LED PAR-56 COB RGB 60W bk

PRO spotlight as DMX model with COB LED

Art. No.: 41607210 GTIN: 4026397461992



The article is no longer in our assortment.

Features:

- Equipped with a high-power RGB 60 W COB LED
- Stepless color blend, color change, dimmer and strobe effect
- Dimmer speed (step response) adjustable
- Stand-alone or DMX mode
- Control panel with LC display for easy configuration
- Locking possibility at the mounting bracket
- With color filter frame
- Various versions available
- 1 powerful LED 60 W COB (chip-on-board) 3in1 TCL RGB (homogenous color mix)
- Strobe effect
- Control via DMX; sound to light via microphone
- Preprogrammed in Light J; EASY SHOW 1; LED EASY OPERATOR 4x4; LED EASY OPERATOR 4x6; LED EASY OPERATOR DELUXE; Light Captain
- With a beam angle of 30°

Technical specifications:

Power supply:	230 V AC, 50 Hz
Power consumption:	85 W
IP classification:	IP20
Protection class:	Protection class I
Power connection:	Fixed power supply cord with safety plug



EAN / GTIN: 4026397461992 Weight: 3,30 kg Length: 0.24 m Width: 0.24 m Heigth: 0.44 m

Eurolite®, Futurelight®, PSSO®, Roadinger®, Alutruss®, Europalms® and Dimavery® are trademarks of Steinigke Showtechnic GmbH, Andreas-Bauer-Straße 5, DE-97297 Waldbüttelbrunn All rights reserved. Subject to change without notice. Errors and omissions excepted.Illustration only. Actual item may differ from photo.

Cable length:	Approx. 1 m
Lamp type:	LED lamp
LED type:	1 x 60 W COB (chip-on-board) 3in1 TCL RGB (homogenous color mix)
DMX channels:	3; 5
DMX input:	1 x 3-pin XLR (M) mounting version
DMX output:	1 x 3-pin XLR (F) mounting version
Control:	DMX; sound to light via microphone
Preprogrammed in:	Light ´J; EASY SHOW 1; LED EASY OPERATOR 4x4; LED EASY OPERATOR 4x6; LED EASY OPERATOR DELUXE; Light Captain
Beam angle:	30°
Beam angle (1/2 peak):	30°
Housing color:	Black
Dimensions:	Width: 23,5 cm Depth: 32,5 cm Height: 36 cm
Weight:	2,90 kg
Legal specifications	
Special product:	Not designed for household room illumination
Intended use:	Show effect lighting