

## EUROLITE LED PAR-56 COB RGB 100W sil

PRO spotlight as DMX model with COB LED

Art. No.: 41607245

GTIN: 4026397454253



**The article is no longer in our assortment.**

### Features:

- Equipped with a powerful RGB 100 W COB LED
- Functions: static colors, RGB color mixture, internal programs, dimmer and strobe settings via DMX, Master/Slave
- Dimmer speed (step response) adjustable
- Operable in stand-alone mode or with DMX interface
- Adjustable microphone sensitivity via LCD display
- Comfortable addressing and setting via control panel with LCD display and four operating buttons
- Locking possibility at the mounting bracket
- With color filter frame
- Ready for connection via power cord with safety-plug
- Available in silver or in black
- 1 powerful LED 100 W COB (chip-on-board) 3in1 TCL RGB (homogenous color mix)
- Strobe effect
- Control via DMX; sound to light via microphone
- Preprogrammed in EASY SHOW 1; LED PC-Control 512; Light´J; LED EASY OPERATOR 4x4; LED EASY OPERATOR 4x6; LED EASY OPERATOR DELUXE
- With a beam angle of 40°
- For further information about this product, please refer to the Data Sheet under "Downloads"

### Logistic

EAN / GTIN: 4026397454253

Weight: 3,00 kg

Length: 0.24 m

Width: 0.24 m

Height: 0.45 m

### Technical specifications:

Power supply: 230 V AC, 50 Hz

Power consumption: 130 W

IP classification:	IP20
Power connection:	Fixed power supply cord with safety plug
Lamp type:	LED lamp
LED type:	1 x 100 W COB (chip-on-board) 3in1 TCL RGB (homogenous color mix)
DMX channels:	3; 5
DMX input:	1 x 3-pin XLR (M) mounting version
DMX output:	1 x 3-pin XLR (F) mounting version
Control:	DMX; sound to light via microphone
Preprogrammed in:	EASY SHOW 1; LED PC-Control 512; Light´J; EASY SHOW 1; LED EASY OPERATOR 4x4; LED EASY OPERATOR 4x6; LED EASY OPERATOR DELUXE
Beam angle:	40°
Beam angle (1/2 peak):	40°
Housing color:	Silver
Dimensions:	Width: 24 cm Depth: 36,5 cm Height: 31,5 cm
Weight:	2,6 kg
Legal specifications	
Special product:	Not designed for household room illumination
Intended use:	Show effect lighting