

FUTURELIGHT DJ-LED Scan 100

Flower matrix scanner with 16 different patterns in 3 colors

Art. No.: 51839175

GTIN: 4026397263367



The article is no longer in our assortment.

Features:

- Gobo rotation via LED matrix
- Strobe effect with adjustable speed
- Equipped with 40 LEDs: 16 x red, 12 x blue, 12 x green
- Long LED life
- 6.3 mm jack socket for remote control
- Fuzzy sound control: program continues automatically during periods without music or bass-beat
- Positioning within 160° Pan and 80° Tilt
- DMX-controlled operation or stand-alone operation with Master/Slave function (up to 4 slaves)
- Blackout, Gobos and Auto/Manual Mode applicable in Stand Alone mode via optional FUTURELIGHT Easy-4 remote control
- Sound-controlled via built-in microphone
- Microphone-sensitivity adjustable via rotary-control
- Control board with 4-digit display
- Advantages of LED technology: long life, low power consumption, minimal heat emission, defacto maintenance free with brilliant light radiation
- DMX control via every standard DMX controller
- 40 powerful LEDs
- The device is cooled by passive convection cooling
- Control via DMX; stand-alone; sound to light via microphone

Logistic

EAN / GTIN: 4026397263367

Weight: 4,10 kg

Length: 0.45 m

Width: 0.23 m

Height: 0.21 m

Technical specifications:

Power supply:

230 V AC, 50 Hz

Power consumption:	23 W
IP classification:	IP20
Lamp type:	LED lamp
LED type:	40
Max. TILT movement:	80° positioning
Max. PAN movement:	160° positioning
Flash rate:	1 - 18 Hz
DMX channels:	5
Cooling:	Passive convection cooling
Control:	DMX; stand-alone; sound to light via microphone
Housing color:	Alu colored
Dimensions:	Width: 19 cm Depth: 38 cm Height: 25,5 cm
Weight:	3,60 kg
DMX channels:	5
DMX connection:	3-pin XLR
Sound-control:	via built-in microphone
Flash-rate:	18 Hz
LED number:	40
Dimensions (L x W x H):	380 x 190 x 255 mm
Legal specifications	
Special product:	Not designed for household room illumination
Intended use:	Show effect lighting