

## FUTURELIGHT DJ-LED Scan 15

DJ scanner with 15 W LED

Art. No.: 51839181

GTIN: 4026397460896



**The article is no longer in our assortment.**

### Features:

- Equipped with a white 15 W LED
- Dimmer
- Manual focus
- Internal programs
- Strobe effect with adjustable speed
- Fuzzy sound control: program continues automatically during periods without music or bass-beat
- Sound-controlled via built-in microphone
- Microphone-sensitivity adjustable via rotary-control
- Positioning within 180° PAN and 80° TILT
- DMX-controlled operation or stand-alone operation with Master/Slave function
- Comfortable addressing and setting via control panel with LED display and three operating buttons
- DMX control via every standard DMX controller
- 1 powerful LED
- Gobo wheel with rotating gobos
- Color wheel with 7 dichroic filters plus open<BR>rainbow effect with adjustable speed in both directions
- Gobo wheel with rotating gobos, 7 gobos and open<BR>shake effect
- Control via sound to light via microphone
- With a beam angle of 15°

### Logistic

EAN / GTIN: 4026397460896

Weight: 4,30 kg

Length: 0.42 m

Width: 0.22 m

Height: 0.27 m

## Technical specifications:

Power supply:	230 V AC, 50 Hz
Power consumption:	45 W
LED type:	1
Max. TILT movement:	80° positioning
Max. PAN movement:	180° positioning
Equipment:	Gobo wheel with rotating gobos
Color generation:	Color wheel with 7 dichroic filters plus open Rainbow effect with adjustable speed in both directions
Gobos:	Gobo wheel with rotating gobos, 7 gobos and open Shake effect
DMX channels:	8
Control:	Sound to light via microphone
Beam angle:	15°
Beam angle (1/2 peak):	15°
Color:	Black
Dimensions:	Width: 35,5 cm Depth: 13,5 cm Height: 25 cm
Weight:	3,91 kg
DMX channels:	8
DMX connection:	3-pin XLR
Sound-control:	via built-in microphone
LED number:	1
LED type:	15 W, white, LedEngin
Color-wheel:	7 dichroic + white
Gobo-wheel:	7 static + open
Dimensions (L x W x H):	355 x 135 x 250 mm
Legal specifications	
Special product:	Not designed for household room illumination
Intended use:	Show effect lighting