

FUTURELIGHT POS-12 LED QCL Powerstick

LED color changing bar with 8 W RGBW LEDs (4in1)

Art. No.: 51841366

GTIN: 4026397504507



The article is no longer in our assortment.

Features:

- Equipped with 12 QCL LEDs in the colors red, green, blue and white
- 4, 6, 10, 48 or 52 DMX channels selectable
- Each LED can be controlled individually
- Hanging as well as standing installation possible
- Functions: RGBW color mixture, color presets, 11 preset color temperatures, automatic color change, built-in programs, dimmer, strobe effect, sound-control, Master/Slave operation
- Dimmer speed (step response) adjustable
- Sound-controlled via built-in microphone
- Adjustable microphone sensitivity via Control Board
- DMX-controlled operation or stand-alone operation with Master/Slave function
- Comfortable addressing and setting via Control Board with LCD display and four operating buttons
- Switch-mode power supply, automatic power supply adaption between 100 and 240 Volts without power selector
- Power connection via Neutrik PowerCon jack and included power cable
- Feed-through output allows to power another device
- After every 8 devices the fixtures must have a renewed connection with the power mains
- DMX control via every standard DMX controller
- Control via stand-alone; DMX
- Preprogrammed in Light´J; LED PC-Control 512

Logistic

EAN / GTIN: 4026397504507

Weight: 5,65 kg

Length: 1.05 m

Width: 0.15 m

Height: 0.19 m

Technical specifications:

Power supply: 100-240 V AC, 50/60 Hz

Power consumption:	105,00 W
IP classification:	IP20
Lamp type:	LED lamp
Control:	Stand-alone; DMX
Preprogrammed in:	Light'J; LED PC-Control 512
Beam angle (1/2 peak):	22°
Housing color:	Black
Dimensions:	Length: 1,041 m Depth: 6,5 cm Height: 16,2 cm
Weight:	5,10 kg
DMX channels:	4/6/10/48/52
DMX connection:	3-pin XLR
Sound-control:	via built-in microphone
Flash-rate:	30 Hz
LED type:	8 W QCL
LED number:	12
Beam angle:	22°
Dimensions (L x W x H):	1041 x 65 x 162 mm
Legal specifications	
Special product:	Not designed for household room illumination
Intended use:	Show effect lighting