

FUTURELIGHT PRO Slim PAR-12 HCL

PRO slimline LED spot with 10 W 6in1 LEDs

Art. No.: 51842560 GTIN: 4026397512540











The article is no longer in our assortment.

Features:

- Equipped with 12 HCL LEDs in the colors red, green, blue, amber, white and UV
- Flat housing form requires minimal space when rigging
- Extremely compact housing in a beautiful design
- Second mounting bracket for safe standing installation
- Locking possibility at the brackets with large metal butterfly screws
- Convection cooling entirely via cooling ribs, no fans, particularly quiet during operation
- Functions: static colors, RGBAW+UV color mixture, color presets, preset color temperatures, automatic color change, built-in programs, dimmer, strobe effect, sound-control, Master/Slave operation
- HSV, HSI, 6, 8 or 12 channels selectable
- Dimmer speed (step response) adjustable
- Sound-control via built-in microphone
- Adjustable microphone sensitivity
- Comfortable addressing and setting via Control Board with four operating buttons and LC display
- Operable in stand-alone mode or via DMX
- Switch-mode power supply for operation between 100 and 240 volts
- Power connection via Neutrik PowerCon jack and included power cable
- Feed-through output allows to power up to 8 devices
- DMX control via every standard DMX controller
- 12 powerful LEDs
- Preprogrammed in Light'J; Light Captain
- Flicker-free

Logistic

EAN / GTIN: 4026397512540

Weight: 6,00 kg Length: 0.38 m Width: 0.38 m Heigth: 0.21 m

Technical specifications:

Power supply:	100-240 V AC, 50/60 Hz
Power consumption:	95 W
LED type:	12
Preprogrammed in:	Light´J; Light Captain
Projection:	Flicker-free
Beam angle (1/10 peak):	33°
Color:	Black
Dimensions:	Width: 29,8 cm Depth: 11,2 cm Height: 32,3 cm
Weight:	5 kg
DMX channels:	HSV/HSI/6/8/12
DMX connection:	5-pin and 3-pin XLR
Sound-control:	via built-in microphone
LED type:	10 W HCL
LED number:	12
Beam angle:	23°
Dimensions (W x D x H):	298 x 112 x 323 mm
Legal specifications	
Special product:	Not designed for household room illumination
Intended use:	Show effect lighting