

FUTURELIGHT PRO Pixel Slim PAR-24 TCL

PRO slimline LED spot with 3 W 3in1 LEDs

Art. No.: 51842625

GTIN: 4026397457544



The article is no longer in our assortment.

Features:

- Equipped with 24 TCL LEDs in the colors red, green and blue
- Each LED can be controlled individually
- 3, 5, 9, 12 or 72 DMX channels selectable for various applications
- Flat housing form requires minimal space when rigging
- Extremely compact housing in a beautiful design
- Second mounting bracket for safe standing installation
- Locking possibility at the brackets with large metal butterfly screws
- Convection cooling entirely via cooling ribs, no fans
- Functions: static colors, RGB color mixture, preset color temperatures, automatic color change, built-in programs, dimmer, strobe effect, sound-control, Master/Slave operation
- Dimmer speed (step response) adjustable
- Sound-controlled via built-in microphone
- Microphone-sensitivity adjustable via rotary-control
- Comfortable addressing and setting via Control Board with four operating buttons and LED display with four-digit 14-segment display
- Operable in stand-alone mode or via DMX
- Master/Slave for parallel operation of several devices
- Power connection via Neutrik PowerCon jack and included power cable
- Feed-through output allows to power another device
- After every 8 devices the fixtures must have a renewed connection with the power mains
- DMX512 control via regular DMX-controller
- Preprogrammed in Light 'J; Light Captain

Logistic

EAN / GTIN: 4026397457544

Weight: 6,85 kg

Length: 0.41 m

Width: 0.41 m

Height: 0.18 m

Technical specifications:

Power supply:	230 V AC, 50 Hz
Power consumption:	120,00 W
Preprogrammed in:	Light´J; Light Captain
Dimensions:	Width: 34,5 cm Depth: 10 cm Height: 36,5 cm
Weight:	6,15 kg
DMX channels:	3/5/9/12/72
DMX connection:	3-pin XLR
Sound-control:	via built-in microphone
LED type:	3 W TCL
LED number:	24
Beam angle:	13°
Dimensions (L x W x H):	100 x 345 x 365 mm
Legal specifications	
Special product:	Not designed for household room illumination
Intended use:	Show effect lighting