

EUROLITE LCD-4 MP/S Dimmer controller

4-channel lighting controller

Art. No.: 70062666

GTIN: 4026397182576



The article is no longer in our assortment.

Features:

- 4 channels
- Fade Time fader with LED for adjusting the step time
- Master-fader with LED for adjusting the total output level
- Audio-fader with LED for adjusting the music sensitivity
- Flash-button per channel and master-flash (Full On-button)
- LED-display of all modes
- 0/10 V-output via one 8-pin DIN-socket
- 42 built-in programs
- Dimmer: Manual control of the channels via sliders
- Full On: all channels can be switched on together
- Program speed adjustable via speed-fader or Tap Sync-button
- Sound-control via external signal or integrated microphone
- Sound to light via RCA socket
- Outputs via 4 safety sockets or two industrial sockets
- Rack installation with 3 units

Logistic

EAN / GTIN: 4026397182576

Weight: 5,70 kg

Length: 0.52 m

Width: 0.20 m

Height: 0.22 m

Technical specifications:

Power supply: 230 V AC, 50 Hz

Dimensions: Width: 48,3 cm
Depth: 14,5 cm
Height: 13,35 cm

Max. power output: 3680 W

Max. current:	16 A
Number of control channels:	4
Max. output/channel:	1150 W
Max. current/channel:	5 A
Integrated programs:	42
Sound-control:	via built-in microphone or via audio-input
Audio-input:	RCA socket
Audio-sensitivity:	0.1-1 V
Output sockets:	4 safety sockets, two 6-pin sockets
Dimensions (W x D x H):	482 x 200 x 132 mm
	Rack installation with 3 u
Minimum mounting depth:	230 mm
Weight:	4.5 kg