

EUROLITE DTB-403/short MK2 Dimmerbar

Chaser bar for trouble-free installations

Art. No.: 70064440 GTIN: 4026397216820





The article is no longer in our assortment.

Features:

- Makes the installation of your lighting system really easy
- Installed directly on the stand or crossbeam
- With 4 spot connections
- Outputs via 4 safety sockets
- 10 pre-programmed chaser-patterns
- Chaser-speed controllable or sound-controlled
- Sound-control via built-in microphone
- Only for professional use
- Control via stand-alone

Package contents

1 x remote control

Technical specifications:

| Power supply: | 230 V AC, 50 Hz |
|-------------------|---|
| Output power: | Max. 3680 W Max. 1150 W per channal |
| Output current: | Max. 5 A per channal |
| Power output: | 6 x Safety contact (F), hinged lid mounting version |
| Control: | Stand-alone |
| Control channels: | 4 |

Logistic

EAN / GTIN: 4026397216820

Weight: 3,60 kg Length: 0.74 m Width: 0.28 m Heigth: 0.13 m

| Color: | Black |
|----------------------------------|--------------------------------|
| Dimensions: | Width: 67,5 cm |
| | Depth: 7,5 cm |
| | Height: 21 cm |
| Weight: | 3,25 kg |
| Remote control | |
| Battery: | 2 x Micro (AAA) (not included) |
| Max. total current: | 16 A |
| Max. output/channel: | 1150 W |
| Max. current/channel: | 5 A |
| Fuse: | F 6.3 A, 250 V |
| Maximum load per fixation point: | 4 kg |
| Max. spaced braceload: | 16 kg |
| Max. centered braceload: | 25 kg |
| TV spigot: | D = 28 mm |
| Max. service life: | 10 years |