

EUROLITE QuickDMX Wireless Receiver

Compact wireless DMX receiver 2.4 GHz

Art. No.: 70064701

GTIN: 4026397509533



Description:

Compact DMX Wireless System 2.4 GHz

The Eurolite QuickDMX transmitter and receiver is used for wireless transmission of DMX512 signals. The complete technology is integrated in an extended 3-pin XLR connector (female) with a rotatable antenna.

The device is constructed as a transceiver, so it can be used as any transmitter and receiver. The use of this device eliminates the necessity of time-consuming cabling between the DMX lighting control unit and the DMX-controlled devices.

Due to the GFSK technology (Gaussian Frequency Shift Keying), interference-free operation is also possible besides other wireless Bluetooth and WiFi devices.

The range is up to 400 meters with visual contact.

Setup is very easy via Plug & Play with a button for connecting and disconnecting QuickDMX receivers.

Logistic

EAN / GTIN: 4026397509533

Weight: 0,23 kg

Length: 0.14 m

Width: 0.12 m

Height: 0.06 m

Features:

- User-friendly 3-pin XLR adapter (female) with swivel antenna
- Wireless DMX eliminates extensive cabling between DMX controller and the DMX-controlled units in lighting installations
- Due to GFSK modulation with 78 channels, interference-free operation also alongside other QuickDMX transceiver and wireless devices in the 2.4 GHz band (e.g. Wi-Fi and Bluetooth)
- 1 to 512 QuickDMX receivers can be controlled by each transmitter
- LED indication for functions
- Transceiver, to be used as transmitter or receiver
- Can receive and process up to 512 DMX channels

- Control via QuickDMX; plug and play
- Operating range up to 400m
- Up to 6 transmitters can be operated in parallel without interference

Technical specifications:

Power supply:	100-240 V AC, 50/60 Hz 5V DC 1000 mA
IP classification:	IP20
Power connection:	Mains input via coaxial power connector (M) mounting version power supply cord for USB A mains connection (provided)
DMX channels:	Input 512
DMX output:	3-pin XLR (F)
Control:	QuickDMX; plug and play
Range:	Range up to 400m
Carrier frequency:	2.4 GHz
Parallel mode:	Max. 6 transmitter
RF power output:	19 dBm
Modulation:	GFSK
Color:	Silver
Dimensions:	Length: 21.2 cm Diameter: Ø 1.8 cm
Weight:	0.16 kg

Scope of delivery:

- 1 x device
- 1 x user manual
- 1 x declaration of conformity
- 1 x external mains adapter
- 1 x USB cable