

QuickDMX Wireless receiver phantom-power

Compact wireless DMX receiver 2.4 GHz, phantom powered

Art. No.: 70064702

GTIN: 4026397513073



List price: 117.81 €
incl. 19% VAT.

QuickDMX Wireless receiver phantom-power

Compact wireless DMX receiver 2.4 GHz, phantom powered

Art. No.: 70064702

GTIN: 4026397513073

Features:

- User-friendly 5-pin XLR plug (female) with swivel antenna
- Wireless DMX eliminates extensive cabling between DMX controller and the DMX-controlled units in lighting installations
- Due to GFSK modulation with 78 channels, interference-free operation also alongside other QuickDMX receivers and wireless devices in the 2.4 GHz band (e.g. Wi-Fi and Bluetooth)
- 1 to 512 QuickDMX receivers can be controlled by each transmitter
- Plug & Play: quick and easy setup with one operating button for connecting/disconnecting QuickDMX receivers
- LED indication for functions
- Transceiver, to be used as transmitter or receiver
- Requires 5 V phantom power for operation
- 2.4 GHz - license-free worldwide
- Can receive and process up to 512 DMX channels
- Controlling by DMX; QuickDMX built-in
- Use a operating range up to 400m