

EUROLITE QuickDMX USB Wireless Transmitter/Receiver

Wireless miniature DMX transceiver 2.4 GHz, phantom powered

Art. No.: 70064704

GTIN: 4026397642131



List price: 53.43 €

incl. 19% VAT.

Features:

- User-friendly USB plug with swivel antenna
- Wireless DMX eliminates extensive cabling between DMX controller and the DMX-controlled units in lighting installations
- Due to GFSK modulation with 78 channels, interference-free operation also alongside other QuickDMX receivers and wireless devices in the 2.4 GHz band (e.g. Wi-Fi and Bluetooth)
- Operating range up to 400 m (with line-of-sight)
- Simultaneous operation of up to 6 transmitters, thus control of 6 DMX universes (3072 DMX channels) possible
- Plug & Play: quick and easy setup with one operating button for connecting/disconnecting QuickDMX receivers
- LED indication for functions
- Transceiver to be used as transmitter or receiver
- Requires 5 V phantom power for operation
- 2.4 GHz ISM band - license-free worldwide
- Can receive and process up to 512 DMX channels
- Can transmit up to 512 DMX channels
- Controlling by DMX; QuickDMX built-in

Logistic

EAN / GTIN: 4026397642131

Weight: 0,04 kg

Length: 0.11 m

Width: 0.08 m

Height: 0.03 m

Technical specifications:

Power supply:	5 V DC
IP classification:	IP20
Power connection:	Mains input USB A (M) connectable version

DMX channels:	Input 512 Output 512
DMX output:	1 x USB, type A
Control:	DMX; QuickDMX built-in
Carrier frequency:	2,4 GHz
Modulation:	GFSK
Parallel mode:	Max. 6 transmitter
Color:	Black
Dimensions:	Width: 8,6 cm Depth: 4 cm Height: 1,1 cm
Weight:	10 g