

EUROLITE QuickDMX USB Wireless Transmitter/Receiver

Wireless miniature DMX transceiver 2.4 GHz, phantom powered

Art. No.: 70064704

GTIN: 4026397642131



Features:

- User-friendly USB plug with swivel antenna
- Wireless DMX eliminates extensive cabling between DMX controller and the DMX-controlled units in lighting installations
- Due to GFSK modulation with 78 channels, interference-free operation also alongside other QuickDMX transceiver and wireless devices in the 2.4 GHz band (e.g. Wi-Fi and Bluetooth)
- LED indication for functions
- Transceiver, to be used as transmitter or receiver
- Requires 5 V phantom power for operation
- Can receive and process up to 512 DMX channels
- Can transmit up to 512 DMX channels
- Control via DMX; QuickDMX; plug and play
- Operating range up to 400m with line-of-sight
- Up to 6 transmitters can be operated in parallel without interference

Logistic

EAN / GTIN: 4026397642131
Weight: 0,04 kg
Length: 0.11 m
Width: 0.08 m
Heigh: 0.03 m

Technical specifications:

Power supply:	5V DC
IP classification:	IP20
Power connection:	Mains input via USB A (M) connectable version
DMX channels:	Input 512 Output 512
DMX output:	1 x USB, type A

Control:	DMX; QuickDMX; plug and play
Range:	Range up to 400m with line-of-sight
Carrier frequency:	2.4 GHz
Parallel mode:	Max. 6 transmitter
RF power output:	19 dBm
Modulation:	GFSK
Color:	Black
Dimensions:	Width: 8.6 cm Depth: 4 cm Height: 1.1 cm
Weight:	0.01 kg

Scope of delivery:

1 x device
1 x user manual
1 x declaration of conformity