eurolite®

EUROLITE Artnet-DMX Node 8

Art-Net/DMX converter with 8 universes





The article is no longer in our assortment.

Features:

- Distributes Art-Net data to 8 DMX512 universes (4096 channels)
- Parallel DMX input possible (1024 channels)
- 8 XLR plugs (3-pin) for DMX output
- 2 XLR jacks (3-pin) for DMX input
- Ethernet port: RJ45, 10/100 Mbps
- User-friendly configuration directly at the front panel via 4 operating buttons and alphanumeric LCD screen (2 x 16 characters)
- LED indication for functions
- Splitter operation possible
- Rack installation 1 U

Technical specifications:

Power supply:	100-240 V AC, 50/60 Hz	
Power consumption:	6,00 W	
Dimensions:	Width: 48,3 cm	
	Depth: 18 cm	
	Height: 4,45 cm	
DMX512 inputs:	2 x 3-pin XLR male	
DMX512 outputs:	8 x 3-pin XLR female	
Ethernet:	RJ45 10/100 Mbps	

Logistic

EAN / GTIN: 4026397508369 Weight: 2,35 kg Length: 0.56 m Width: 0.23 m Heigth: 0.10 m

Eurolite®, Futurelight®, PSSO®, Roadinger®, Alutruss®, Europalms® and Dimavery® are trademarks of Steinigke Showtechnic GmbH, Andreas-Bauer-Straße 5, DE-97297 Waldbüttelbrunn All rights reserved. Subject to change without notice. Errors and omissions excepted.Illustration only. Actual item may differ from photo.

Protocol:	Art-Net 3
Dimensions (L x W x H):	483 x 180 x 50 mm
Weight:	2 kg