

## OMNITRONIC EIO3-50II Amplifier 50W

PA mixing amplifier with tuner and CD player

Art. No.: 80709872

GTIN: 4026397309386



**The article is no longer in our assortment.**

### Features:

- 1 x 50 W RMS amplifier power
- Integrated FM/AM tuner with 24 memory places and station finding
- Integrated CD/MP3 player
- Audio replay of CD-DAs, CD-Rs, CD-RWs
- MP3 replay with a maximum of 999 files, 255 folders per CD
- 10 cm LCD (4") with ID3 tag indication
- 3 microphone inputs (6.3 mm jack) with separate level controls
- Input 1 with priority circuit
- Input 3 switchable to line level
- Siren, switchable
- 2-way tone control (treble, bass)
- 5-fold LED level display
- PA speaker outputs (25V, 50V, 70V, 100V) via terminal blocks
- 4 ohms output for passive speaker
- Protection circuits: over current, short circuit, turn-on delay
- Mains operation or 12 V battery operation
- Rack installation

### Logistic

EAN / GTIN: 4026397309386

Weight: 9,80 kg

Length: 0.55 m

Width: 0.40 m

Heigh: 0.20 m

### Technical specifications:

Power supply: 115/230 V AC, 50/60 Hz

Power consumption: 150,00 W

Frequency range: 80 - 15000 Hz

Dimensions:	Width: 48,3 cm
	Depth: 32 cm
	Height: 8,9 cm
	or 12 V emergency power battery
Output power:	50 W RMS
Output type:	70 V, 100 V or 4 ohms
Mic input:	5 mV, 600 ohms
Output connectors:	Screw connectors
S/N ratio:	105 dB
Tuner AM channel:	522-1,161 Hz
Step pace:	9 kHz
Tuner FM channel:	87-108 Hz
Step pace:	50 kHz
Distortion:	<0.6 %
Slew rate:	70 V/ms
Dimensions:	483 x 320 x 100 mm
Weight:	9 kg