

OMNITRONIC ELA-T50 Transformer 50 W

100 V audio transformer

Art. No.: 80711405
GTIN: 4026397271362



Features:

- For amplifiers or speakers without built-in 100 V audio transformer
- Converts low-impedance signals into 100 V signals
- 5 power taps

Logistic

EAN / GTIN: 4026397271362
Weight: 0,88 kg
Length: 0.10 m
Width: 0.07 m
Height: 0.06 m

Technical specifications:

Power:	Rated: 50W RMS
Frequency range:	30 - 15000 Hz
Impedance:	Public address systems 100V; 4 ohms; 8 ohms; 16 ohms
Power tapping:	6.25W; 12.5W; 25W; 37.5W; 50W RMS via no connector/cable only switchable
Borehole distance:	8.3 cm
Dimensions:	Width: 9.3 cm Depth: 5.7 cm Height: 5.6 cm
Weight:	0.84 kg

Scope of delivery:
