

## OMNITRONIC PM-408 DJ Mixer

PRO 3-channel DJ mixer

Réf. : 10006818

GTIN: 4026397313420



## L'article n'est plus disponible.

### Description:

What do you really need?

A question: Does it makes sense for a housewife to drive an expensive roadster, when the vehicle is mainly used for shopping and transporting the children? Of course not! It would often be wiser to think about necessity and functionality and to set them on top of the list. Something that is true not only for the fields of cars. Our OMNITRONIC PM-408 DJ-Mixer therefor sets a perfect example. So you only need a reliable, solid standard mixer with current standard features and an appealing design? For you three input channels with gain control and a 3-way equalizer, one microphone channel with a 2-way equalizer and talkover function, a replaceable crossfader, super-smooth channel faders, a 10-digit stereo LED level meter and master level control, two switchable line/phono inputs and a headphone input of course are enough? Then the PM-404 is your choice. Because this mixer is an uncomplicated and unexpensive alternative for the home mixing area as well as for a bar with DJ. The own demand surely is he decisive factor. But sometimes it doesn't need to be more!

### Caractéristiques:

- 3 input channels with gain control and 3-way equalizer, channel 1 and 3 with kill function
- Talkover button for the DJ microphone channel
- Pre-fader listening (CUE) to the stereo input channels via adjustable headphone output
- Replaceable crossfader for crossfading between input channels
- High-quality and super-smooth channel faders
- 10-digit stereo LED level meter, master level control and booth level control
- Inputs: 4 x line (stereo RCA), 2 x phono/line (stereo RCA), switchable; DJ microphone and headphones (both 6.3 mm jack)
- Outputs: master (3-pin XLR, stereo RCA), booth and record (both stereo RCA)

### Logistique

EAN / GTIN: 4026397313420

Poids: 3,60 kg

Longueur: 0,39 m

Largeur: 0,27 m

Hauteur: 0,14 m

## Données techniques:

Alimentation électrique:	230 V AC, 50 Hz
Puissance totale de raccordement:	5,00 W
Branchement électrique:	Alimentation électrique via Appareils froids (M) version encastrable Câble d'alimentation à prise contact de protection (inclus dans la livraison)
Plage de fréquence:	20 - 20000 Hz
Dimension:	Largeur : 25,5 cm Profondeur : 26,2 cm Hauteur : 11 cm
Poids:	3,30 kg
Inputs:	
DJ microphone:	6.3 mm jack
Minimum input voltage:	1.5 mV RMS/ 1 kohm
LINE 1-6:	stereo RCA
Minimum input voltage:	150 mV RMS/ 270 kohm
PHONO 1-2:	stereo RCA
Minimum input voltage:	3 mV RMS/ 470 kohm
Outputs:	
MASTER:	stereo RCA, stereo XLR (3-pin)
BOOTH:	stereo RCA
Max. output level:	+22 dBu
Output voltage:	9 V RMS
REC:	stereo RCA
Output voltage:	225 mV RMS/ 5 kohm
Headphones output:	6.3 mm stereo jack, 16 ohms
Tone control:	
3 x High:	-12 dB to +12 dB/ 1 kHz
3 x Middle:	-12 dB to +12 dB/ 1 kHz
3 x Low:	12 dB to +12 dB/ 1 kHz
S/N ratio:	>80 dB
Distortion:	0.05% (line/phono)