

INTUSONIC PAA71 microphone-mixeur de ligne

Mélangeur micro/ligne, 7 canaux

Réf. : 12604176

GTIN: 5060502923219



Prix de catalogue: sur demande €

TVA 19% incl.

Description:

The INTUWORX PAA71 is 7-channel mic/line mixer and the perfect center of any installed sound system. It offers 5 multi-purpose inputs which can either be fed with a balanced microphone signal or an unbalanced stereo line signal. One further balanced stereo line level input is specifically useful for sources at larger distance, like a mixer on a stage, or the output of a secondary room's system. The same input can be switched to receive its input signal from the 3.5mm TRS jack on the front, or the built-in LINKOUSTIC 4.2 wireless audio link. An additional dedicated microphone input with adjustable talkover (priority) provides control over announcements. Every input -- with the exception of the balanced stereo input -- is equipped with rear-panel gain control and a front-panel 2-band equalizer. The external shutdown and emergency signal input connections allow integration with central announcement and evacuation systems where required.

Logistique

EAN / GTIN: 5060502923219

Poids: 3,25 kg

Longueur: 0.54 m

Largeur: 0.33 m

Hauteur: 0.10 m

Caractéristiques:

- (19") 48,3 cm installation en rack
- Vous trouverez de plus amples informations sur ce produit dans la rubrique « Téléchargements » de la fiche technique

L'étendue des fournitures

- 1 x mode d'emploi, 1 x table de mixage, 1 x câble secteur/câble d'alimentation, 10 x borne enfichable à vis, 1 x prise, 4 x pied, 1 x antenne

Données techniques:

Alimentation électrique: 115/230 V CA, 50/60 Hz

Puissance totale de raccordement: Max. 12 W

Classe de protection:	SK I
Branchement électrique:	Alimentation électrique via Appareils froids (M) Câble d'alimentation à prise contact de protection (inclus dans la livraison)
Plage de fréquence:	20 - 20000 Hz
Rapport signal/bruit:	>82 dB Line
Distorsion harmonique:	<0,05 % avec 1 kHz
Alimentation fantôme:	Ou 12 V DC
Connexions:	Entrée: 1 x Câble jack 6,3 mm (sym.)
Canaux:	Canal d'entrée: 5 x Stéréo avec Interrupteur Mic-Line via RCA, réglage du canal via Bouton rotatif, Régulateur 2 bandes EQ
Égaliseur:	1 x Régulateur 2 bandes Mono
Conception du boîtier:	(19") 48,3 cm installation en rack
Dimension:	Largeur : 48,3 cm Profondeur : 19 cm Hauteur : 4,4 cm
Poids:	2,70 kg