

## OMNITRONIC Set CMX-2000 + 2x DJS-2000

Set with two media players and one mixer (midi controller)

Réf. : 20000394

GTIN:



### Caractéristiques:

- 2-channel DJ mixer/MIDI controller bundled with Virtual DJ
- Optimized layout for Virtual DJ and Traktor PRO 2 - Virtual DJ 7 LE voucher included
- Traktor PRO 2 and Serato Scratch Live mappings available with full support for scratch and sample decks
- Flexibly combines stand-alone mixing of analog sources with MIDI control for DJ software
- Built-in DVS audio system for direct use of timecode systems with vinyl or CD in Virtual DJ and other open applications via USB
- 2 input channels with routing facility for analog inputs and MIDI decks as desired
- Full-fledged MIDI sections with 2 layers for 4-deck control
- Perfect MIDI control for file browsing, transportation, hot cues, samples, sample recorder, loops, effects, pitch und video transitions
- Advanced setup options for scratch DJs: crossfader and channel faders with adjustable curve and reverse selectors
- Built-in USB sound card 4 IN/4 OUT
- Supports Mac OSX, Windows XP, Vista, 7
- Professional-grade metal chassis with replaceable crossfader (45 mm)
- 2 line and 2 line/phono RCA inputs for connecting CD players, turntables and other external hardware
- 2 AUX inputs (3.5 mm/6.3 mm jack) connect MP3 players and tablets
- Mic input (XLR/6.3 mm jack) with tone control and talkover
- 2 master outputs (XLR/RCA) for PA applications
- Booth output (RCA), independently adjustable
- 3.5 mm/6.3 mm jack dual headphones output with cue mix control
- Bright color-coded LED buttons provide optimal visual feedback while triggering loops, samples, effects and cue points
- User-definable LED modes for Serato Scratch Live

### Logistique

- Dual-function audio/video crossfader for video performances within Virtual DJ
- 3-band EQ (high, mid, low) and HP/LP filter per channel
- Mixer section switchable between analog mode and MIDI mode
- File selector encoder and 2 load buttons for mouseless music library control
- 8 Hot Cue buttons per channel
- Auto Loop function with Beat Jump (Loop Cut), manual Loop In/Out buttons
- FX/sampler units with 4 parameter controls and 4 buttons per channel
- Various controls for GUI, mixer and video
- Shift button for various dual-button operations
- Separate VU meters for master and PFL signal
- Crossfader with faderstart function for compatible CD players
- Compatible to any MIDI-controlled DJ software including Serato Scratch Live, Traktor, Ableton Live
- All MIDI control elements can be edited and freely assigned
- ASIO drivers with minimum latency and high-quality audio characteristics available for download (PC)
- L'appareil peut être connecté au PC via USB, Connecté à Virtual DJ<BR>compatible midi
- <p>OMNITRONIC DJS-2000 DJ Player
- <h2 class="featureSatz">Media player and MIDI controller for DJs</h2>Anti-shock, DSP and internal memory
- Audio CD/CD-R/CD-RW/MP3 CD
- 2 USB ports for storage media and portable players (FAT 32)
- USB audio link: two connected players can play music from one USB device
- Controls any MIDI-compatible DJ software (e.g. Traktor)
- All control elements are MIDI compatible and can be freely edited and assigned
- Control of 2 virtual decks with a single DJS-2000
- Access music files more easily and quickly via smart music database management with free PC software Database Builder
- Sort USB devices lightning-fast by title, artist, album and genre
- Instant start within 10 ms
- 10 seconds anti-shock protection
- Bright dot-matrix VFD display for all functions
- Touch-sensitive jog wheel with adjustable sensitivity and mode selector: scratch, pitch bend and auto cue scratch
- Jog wheel with adjustable LED illumination
- Start and brake speed adjustable
- DSP with beat-synchronized effects (echo, flanger, filter), parameters adjustable
- Automatic beat counter (switchable to manual operation)
- Sampler unit with 4 banks (4 x 5 seconds)
- Internal memory for 2000 cue points of up to 500 CDs
- 4 hot cues or hot loops
- Auto cue
- Seamless loop/reloop
- Auto loop, beat-synchronized and adjustable
- Master tempo (tonal pitch remains constant when speed is changed)
- Next track search: select next track while playing the current one
- Folder navigation
- Supports ID3 tags
- Supports WAV format
- System menu for user-defined settings
- Extra-long pitch fader
- Pitch adjustment  $\pm 6\%$ ,  $\pm 10\%$ ,  $\pm 16\%$ ,  $\pm 100\%$
- Pitch bend buttons
- Fader start
- Relay play
- Single or continuous play
- Reverse play
- Repeat function (repeat folder)
- Indication of elapsed time, remain time (MP3 files) or total remain time (audio CD)
- Bargraph display
- Slot-in drive
- The Database Builder software is available in the manufacturer's download section
- Processeur de signal numérique mastertempo
- Commandé via MIDI via USB
- Réglage du niveau: CD-DA  $\pm 6\%$ ,  $\pm 10\%$ ,  $\pm 16\%$ ,  $\pm 100\%$
- Réglage du niveau: MP3  $\pm 6\%$ ,  $\pm 10\%$ ,  $\pm 16\%$

- L'appareil peut être connecté au PC via USB, Connecté à Virtual DJ<BR>compatible midi
- Boîtier du pupitre

## Données techniques:

---

Poids: 9,40 kg

---

### OMNITRONIC CMX-2000 2+1-channel MIDI controller

Alimentation électrique:	100-240 V CA, 50/60 Hz
Puissance totale de raccordement:	14 W
Branchement électrique:	Alimentation électrique via appareils froids (M) version encastrable câble d'alimentation à prise contact de protection (inclus dans la livraison)  Tramite
Port USB:	USB 2.0, type B
PC connect:	Virtual DJ via USB Compatible midi
Dimension:	Largeur : 36 cm Profondeur : 26,5 cm Hauteur : 10,5 cm
Poids:	3,90 kg
Inputs:	
Line:	2 x stereo RCA
Line/phono:	2 x stereo RCA, switchable
DJ microphone:	combinaison XLR/6.3 mm jack, bal.
Aux:	3.5 mm jack and stereo RCA
Outputs:	
Master:	XLR L/R and stereo RCA
Booth:	stereo RCA
Headphones output:	3.5 mm and 6.3 mm jack
Converter:	16 bits
Sample rate:	48 kHz
Faderstart:	2 x 3.5 mm jack

### OMNITRONIC DJS-2000 DJ Player

Alimentation électrique:	100-240 V CA, 50/60 Hz
Puissance totale de raccordement:	16,00 W
Plage de fréquence:	17 - 20000 Hz
Rapport signal/bruit:	>126 dB
Distorsion harmonique:	<0,01 % avec 1 kHz
DSP:	Processeur de signal numérique mastertempo
Commande:	MIDI via USB

Lecteur audio:	Lecteur USB + CD, (ID3 tag), Seamless loop, Anti-choc
Lecteur de CD-ROM:	Insertion-lecteur individuel
Écran:	CD-DA ID3-Tags , Temps de lecture du titre , Temps de lecture du titre restant , Temps de lecture restant total; MP3 ID3-Tags , Temps de lecture du titre , Temps de lecture du titre restant
Connexions:	Sortie: Line via 1 x RCA stéréo 2 V Sortie: 1 x RCA stéréo
Format de la musique:	CD, CD-R, CD-RW, CD-DA, MP3; WAV
Précision du châssis:	1/75 s
Appareils de stockage appropriés:	Appareils USB max. 32GB (FAT 32)
Réglage du niveau:	CD-DA $\pm 6\%$ , $\pm 10\%$ , $\pm 16\%$ , $\pm 100\%$ MP3 $\pm 6\%$ , $\pm 10\%$ , $\pm 16\%$
Port USB:	2 x type A
PC connect:	Virtual DJ via USB Compatible midi
Conception du boîtier:	Boîtier du pupitre
Dimension:	Largeur : 21,8 cm Profondeur : 29,6 cm Hauteur : 10,4 cm
Poids:	2,75 kg
Type:	CD/MP3 player and MIDI controller
Channel separation:	91 dB
MIDI connection:	USB type B
Fader start/relay mode:	3.5 mm jack

## Contenu de la livraison:

---