

FUTURELIGHT CP-512 MST Controller 16 bit
Universal DMX controller

Réf. : 51834299
GTIN: 4026397280326



L'article n'est plus disponible.

Caractéristiques:

- 512 control channels for 16 projectors with up to 32 channels
- 16-bit resolution for fine Pan/Tilt movements
- Projector library with up to 255 entries
- 64 programs
- 64 records
- 64 preset scenes, 64 preset macros
- 10 selectable languages
- Mirror movement direction can be inverted
- Copy function for scenes, programs and records
- 99 chasers definable, one chaser per program
- Blackout function
- Sound control via built-in microphone or audio input
- Security code operation
- Operating hour meter
- USB port for firmware updates (available in the download section)
- Rack installation with 6 U
- Peut envoyer jusqu'à 512 canaux DMX
- Commandé via DMX

Logistique

EAN / GTIN: 4026397280326
Poids: 5,40 kg
Longueur: 0.56 m
Largeur: 0.34 m
Hauteur: 0.21 m

Données techniques:

Alimentation électrique:	230 V AC, 50 Hz
Puissance totale de raccordement:	6,00 W
Type de protection:	IP20

Canaux DMX:	Sortie 512
Commande:	DMX
Couleur du boîtier:	Noir
Couleur:	Noir
Dimension:	Largeur : 48,3 cm Profondeur : 17,6 cm Hauteur : 8,9 cm
Poids:	4,50 kg
	via 12 V DC, 500 mA power unit included in the delivery
Number of control channels:	512
Sound-input:	6.3 mm stereo Jack
Audio-sensitivity:	0.3-1 V
DMX512 output:	3-pin XLR connector
Free chasers:	64
Dimensions (LxHxD):	483 x 265 x 83 mm
	Rack installation with 6 u
Minimum mounting depth:	90 mm