

FUTURELIGHT DMD-512 DMX Monitor Driver

Convenient DMX monitor driver

Réf. : 51834650

GTIN: 4026397336047



L'article n'est plus disponible.

Caractéristiques:

- For equipping simple DMX controllers with monitor, mouse, keyboard and PC connection
- 1024 control channels
- 3 working modes: DMX receiver (2 x 512 channels), DMX converter (1 x 512 channels), DMX controller (1024 channels)
- Comfortable adjustment of different parameters
- Change channel values
- Group DMX-channels
- DMX-channels can be inverted
- Include virtual Master Fader
- Built-in clock
- Recommended monitor resolution 1280 x 1024 pixels, 60 Hz
- Peut recevoir et traiter jusqu'à 1024 canaux DMX
- Peut envoyer jusqu'à 1024 canaux DMX
- Commandé via DMX
- Interface
- Made in Europe

Logistique

EAN / GTIN: 4026397336047

Poids: 1,17 kg

Longueur: 0.40 m

Largeur: 0.11 m

Hauteur: 0.09 m

Données techniques:

Alimentation électrique: 230 V AC, 50 Hz

Puissance totale de raccordement: 6,00 W

Type de protection: IP20

Classe de protection: SK III

Canaux DMX:	Entrée 1024 Sortie 1024
Entrée DMX:	2 x XLR (M) 3 broches version encastrable
Sortie DMX:	2 x XLR (F) 3 broches version encastrable
Commande:	DMX
Couleur du boîtier:	Noir
Couleur:	Noir
Conception du boîtier:	Interface
Dimension:	Largeur : 31,5 cm Profondeur : 7,5 cm Hauteur : 6,8 cm
Poids:	1,01 kg