


## FUTURELIGHT PCC-250 PRO-Colour-Changer

Multifunctional color changer

Réf. : 51840900

GTIN: 4026397121469



### Caractéristiques:

- DMX-controlled operation or stand-alone operation with Master/Slave function
- 48 preprogrammed scenes in Program Run for stand-alone operation
- Number of scenes in Program Run can be changed individually
- The scenes in Program Run can be modified via the Control Board or via an external controller and loaded into the memory
- 8 built-in programs can be called up via DMX controller
- Sound-controlled via built-in microphone
- Color wheel with additional 4 discrete dichroic filters plus open, 3200 K and 5600 K correction filters, UV filter
- Switchable color change (mode 1: only full colors, mode 2: color-change at every position)
- Rainbow effect with adjustable speed in both directions
- Beam-shape effect: wide and flat beam can steplessly be rotated by 180°
- Strobe effect of 1-13 flash per sec.
- Lightbeam with 8°-22° radiation angle
- Control board with 4-digit display and foil keyboard for adjusting the DMX-starting address, Program, Reset, lamp on/off
- Remotely switching of the lamp
- Built-in demo sequence
- Remote reset function
- Motorized zoom
- For MSD/HSD 250 or MSD 250/2 lamp
- DMX control via every standard DMX controller
- Vous trouverez de plus amples informations sur ce produit dans la rubrique « Téléchargements » de la fiche technique

### Logistique

EAN / GTIN: 4026397121469

Poids: 15,85 kg

Longueur: 0.45 m

Largeur: 0.38 m

Hauteur: 0.48 m

## Données techniques:

---

Alimentation électrique:	230 V AC, 50 Hz
Puissance totale de raccordement:	440,00 W
Dimension:	Largeur : 32,5 cm Profondeur : 43,5 cm Hauteur : 35 cm
DMX channels:	6
DMX connection:	3-pin XLR
Flash-rate:	13 Hz
Color-wheel:	4 dichroic filters, 3200 K and 5600 K correction-filters, UV-filter and white
Dimensions (L x W x H):	325 x 435 x 350 mm
Weight:	13 kg
Produit spécial:	Non destiné à l'éclairage de la pièce dans les ménages
Utilisation:	Éclairage pour effets de spectacle

## Contenu de la livraison:

---