

## EUROLITE LCD-8 DMX Dimmer controller

Lighting controller 8 channels

Réf. : 70064591

GTIN: 4026397119046



### Caractéristiques:

- Can be used as DMX controller or analog lighting controller (8 channels)
  - 8 channel-faders with LED
  - Fade Time fader with LED for adjusting the step time
  - Master-fader with LED for adjusting the total output level
  - Audio-fader with LED for adjusting the music sensitivity
  - Flash-button per channel and master-flash (Full On-button)
  - LED-display of all modes
  - 0/10 V-output via two 8-pin DIN-sockets
  - 48 built-in programs
  - Dimmer: Manual control of the channels via sliders
  - Full On: all channels can be switched on together
  - Program speed adjustable via speed-fader or Tap Sync-button
  - Sound-control via external signal or integrated microphone
  - External signal connection via RCA socket
  - Power supply via included power unit or via 18-20 V dimmer pack
  - Rack installation
  - Only for professional use
- Appareil**
- Sans fil, flexible et polyvalent

### Logistique

EAN / GTIN: 4026397119046

Poids: 3,35 kg

Longueur: 0.55 m

Largeur: 0.25 m

Hauteur: 0.13 m

### Données techniques:

Alimentation électrique: 230 V AC, 50 Hz

Puissance totale de raccordement: 6,00 W

Dimension:	Largeur : 48,3 cm Profondeur : 13,35 cm Hauteur : 6,5 cm
Type de batterie:	1 x Nickel hydrure métallique 3,6 V, via 15-18 V DC, 300 mA power unit included in the delivery or optional dimmer-pack
Number of control channels:	8
Integrated programs:	48
Sound-control:	via built-in microphone or via audio-input
Audio-input:	RCA
Audio-sensitivity:	0.1-1 V
DMX512 output:	3-pin XLR connector
Analogue output:	2 x 8-pin DIN-socket, 4 channels
Output voltage:	0/10 V DC
Dimensions (L x W x H):	483 x 132 x 65 mm Rack installation with 3 u
Minimum mounting depth:	90 mm
Weight:	2.2 kg

### **Contenu de la livraison:**

1 x Appareil