

## EUROLITE LCD-12 DMX Dimmer controller

Lighting controller 12 channels

Réf. : 70064592

GTIN: 4026397119053



**L'article n'est plus disponible.**

### Caractéristiques:

- Can be used as DMX controller or analog lighting controller
- 12 channel-faders with LED
- Fade Time fader with LED for adjusting the step time
- Master-fader with LED for adjusting the total output level
- Audio-fader with LED for adjusting the music sensitivity
- Flash-button per channel and master-flash (Full On-button)
- LED-display of all modes
- 0/10 V-output via three 8-pin DIN-sockets
- 53 built-in programs
- Dimmer: Manual control of the channels via sliders
- Full On: all channels can be switched on together
- Program speed adjustable via speed-fader or Tap Sync-button
- Sound-control via external signal or integrated microphone
- External signal connection via RCA socket
- Power supply via included power unit or via 18-20 V dimmer pack
- Rack installation
- Only for professional use

#### Appareil

- Sans fil, flexible et polyvalent

#### L'étendue des fournitures

- 1 x appareil

### Logistique

EAN / GTIN: 4026397119053

Poids: 3,10 kg

Longueur: 0.56 m

Largeur: 0.24 m

Hauteur: 0.14 m

## Données techniques:

Alimentation électrique:	230 V AC, 50 Hz
Puissance totale de raccordement:	6,00 W
Dimension:	Largeur : 48,3 cm Profondeur : 13,35 cm Hauteur : 6,5 cm
Appareil	
Type de batterie:	1 x Nickel hydrure métallique 3,6 V, via 15-18 V DC, 300 mA power unit included in the delivery or optional dimmer-pack
Number of control channels:	12
Integrated programs:	53
Sound-control:	via built-in microphone or via audio-input
Audio-input:	RCA
Audio-sensitivity:	0.1-1 V
DMX512 output:	3-pin XLR connector
Analogue output:	3 x 8-pin DIN-socket
Output voltage:	0/10 V DC
Dimensions (L x W x H):	483 x 132 x 65 mm Rack installation with 3 u
Minimum mounting depth:	90 mm
Weight:	2.6 kg