

EUROLITE KRX-16 DMX lighting controller

DMX lighting controller 16 channels

Réf. : 70064620

GTIN: 4026397129816



L'article n'est plus disponible.

Caractéristiques:

- 16 channel-faders with LED
- Fade Time fader with LED for adjusting the step time
- Master-fader with LED for adjusting the total output level
- Audio-fader with LED for adjusting the music sensitivity
- Speed-fader for adjusting the program-speed
- Flash-button per channel and master-flash (Full On-button)
- LED-display of all modes
- 16 freely programmable programs
- Dimmer: Manual control of the channels via sliders
- Full On: all channels can be switched on together
- Program speed adjustable via speed-fader or Tap Sync-button
- Sound-control via external signal or integrated microphone
- Sound to light via RCA socket
- Foot switch connection via 6.3 mm stereo jack plug (1/4")
- Power supply via included power unit
- Rack installation

Logistique

EAN / GTIN: 4026397129816

Poids: 4,65 kg

Longueur: 0.61 m

Largeur: 0.32 m

Hauteur: 0.17 m

Données techniques:

Alimentation électrique: 230 V AC, 50 Hz

Puissance totale de raccordement: 10,00 W

Dimension: Largeur : 48,3 cm
Profondeur : 22,5 cm

| | |
|-----------------------------|--|
| | Hauteur : 8,9 cm |
| | via 12-20 V DC, 500 mA power unit included in the delivery |
| Number of control channels: | 16 |
| Integrated programs: | 16 |
| Sound-control: | via built-in microphone or via audio-input |
| Audio-input: | RCA |
| Audio-sensitivity: | 0.1-1 V |
| DMX512 output: | 3-pin XLR connector with polarity selector |
| Dimensions (L x W x H): | 483 x 222 x 85 mm |
| | Rack installation with 5 u |
| Minimum mounting depth: | 100 mm |
| Weight: | 4.4 kg |