

## EUROLITE CLX-16 DMX lighting controller

DMX lighting controller 16 channels

Réf. : 70064650

GTIN: 4026397129823



**L'article n'est plus disponible.**

### Caractéristiques:

- 8 channel-faders with LED
- 8 channels switchable via Latch-buttons
- Fade Time button for adjusting the step time
- Master-fader with LED for adjusting the total output level
- Audio-control with LED for adjusting the music sensitivity
- Speed-control for adjusting the program-speed
- Flash-button per channel and master-flash (Full On-button)
- LED-display of all modes
- 30 freely programmable programs
- Dimmer: Manual control of the channels via sliders
- Full On: all channels can be switched on together
- Program speed adjustable via speed-fader or Tap Sync-button
- Sound-control via external signal or integrated microphone
- Sound to light via RCA socket
- Foot switch connection via 9-pin Sub-D socket
- Power supply via included power unit

### Logistique

EAN / GTIN: 4026397129823

Poids: 3,15 kg

Longueur: 0.46 m

Largeur: 0.25 m

Hauteur: 0.15 m

### Données techniques:

Alimentation électrique: 230 V AC, 50 Hz

Puissance totale de raccordement: 5,00 W

Dimension:  
Largeur : 32 cm  
Profondeur : 18 cm

	Hauteur : 8 cm
	via 12-20 V DC, 250 mA power unit included in the delivery
Number of control channels:	16
Integrated programs:	30
Sound-control:	via built-in microphone or via audio-input
Audio-input:	RCA
Audio-sensitivity:	0.1-1 V
DMX512 output:	3-pin XLR connector with polarity selector
Dimensions (L x W x H):	320 x 180 x 80 mm
Weight:	2 kg