

## EUROLITE VSD-104 Video distributeur 1in4

Amplificateur de distribution AV à 4 bandes

Réf. : 81013010

GTIN: 4026397279917



### Caractéristiques:

- Distribute audio, composite video and s-video television signals from a single AV source to multiple television monitors
- Daisy-chain several units for larger displays with equal picture quality and save the expense of additional AV receivers
- Typical applications are information systems in shopping centers, schools, hotels, railway stations, airports etc.
- Integrated amplifier for lossless signal transmission
- Signal transmission up to 50 meters
- Additional Aux In for connecting a music source
- 12 V power supply via power unit included in the delivery

### Logistique

EAN / GTIN: 4026397279917

Poids: 0,90 kg

Longueur: 0.31 m

Largeur: 0.13 m

Hauteur: 0.06 m

### Données techniques:

Alimentation électrique: 100-240 V CA, 50/60 Hz

Puissance totale de raccordement: 6,00 W

Plage de fréquence: 20 - 100 Hz

Rapport signal/bruit: >100 dB

Distorsion harmonique: <0,05 % avec 1 kHz

Dimension: Largeur : 24,2 cm  
Profondeur : 12,8 cm  
Hauteur : 5 cm

Poids:	0,77 kg
<hr/>	
Video:	
<hr/>	
1 x input:	1 Vpp/ 75 ohms, composite RCA
<hr/>	
4 x outputs:	1 Vpp/ 75 ohms, composite RCA
<hr/>	
Gain:	2 V, 1 V (terminated)/ 75 ohms
<hr/>	
Return loss:	>18 dB
<hr/>	
Video bandwidth:	>100 MHz
<hr/>	
Audio:	
<hr/>	
2 x inputs:	22 kohms, stereo RCA and 3.5 mm jack (1/8")
<hr/>	
4 x outputs:	1 kohms, stereo RCA
<hr/>	
Gain:	nominal 0 dB
<hr/>	
Channel separation:	>75 dB
<hr/>	

### **Contenu de la livraison:**

---