

## OMNITRONIC MX-410B Multichannel mixer

PRO 4+1-channel mixer

Art.n.: 10006751

GTIN: 4026397312997



**L'articolo non è più disponibile.**

### Features :

- High-grade discotheque mixer with convincing sound and 2 master channels
- 4 channels with gain control, 3-band equalizer, cue button and smooth, durable faders
- 1 DJ microphone channel with 3-band equalizer, level control, on air and talkover selector
- Color illuminated rotary controls and rubber buttons
- Prefader listening to all input channels and the master output via adjustable headphones output, with cue mix/split function and 10-digit LED level meter
- Replaceable crossfader for crossfading between input channels
- 2 separately controllable master channels with mono/stereo selector switch
- Master channel 1 with fader and 10-digit stereo LED level meter, switchable to master channel 2
- 7-band stereo equalizer for master channel 1; assignable to master channel 2 and booth output
- Adjustable monitor output (DJ booth)
- 2 recording outputs, independent of the master and with on/off switch for DJ microphone signals
- Inputs: 10 x line (stereo RCA), additionally 1 x line at the front panel (stereo RCA/3.5 mm jack (1/8")); 2 x phono/line (stereo RCA), switchable; 1 x DJ microphone (XLR/6.3 mm jack), 2 x microphone (6.3 mm jack) and headphones (3.5 mm/6.3 mm jack (1/8"/1/4"))
- Outputs: 2 x master (stereo XLR/stereo RCA), 1 x booth (stereo RCA/6.3 mm stereo jack, bal.) and 2 x record (stereo RCA)
- Operation via supplied power unit
- Available in silver or black
- Rack installation, 5 U
- Montaggio su rack (19") 48,3 cm

### Logistica

EAN / GTIN: 4026397312997

Peso : 5,80 kg

Lunghezza : 0.61 m

Larghezza : 0.27 m

Altezza : 0.15 m

## Dati tecnici :

|                               |                                                                                 |
|-------------------------------|---------------------------------------------------------------------------------|
| Potenza totale installata:    | 30,00 W                                                                         |
| Intervallo di frequenza:      | 20 - 20000 Hz                                                                   |
| Struttura della custodia:     | Montaggio su rack (19") 48,3 cm                                                 |
| Misure:                       | Larghezza: 48,3 cm<br>Profondità: 22 cm<br>Altezza: 8,9 cm                      |
| Peso:                         | 5,25 kg                                                                         |
| Power supply:                 | 230 V AC, 50 Hz,<br>via supplied power unit                                     |
| Inputs:                       |                                                                                 |
| DJ microphone (front):        | combined XLR/6.3 mm jack (1/4") (bal.)                                          |
| DJ microphone (rear):         | 6.3 mm jack (1/4") (bal.)                                                       |
| MIC 1, MIC 2 (rear):          | 6.3 mm jack (1/4") (bal.)                                                       |
| Minimum input voltage:        | 1 mV RMS                                                                        |
| LINE 1-10 (rear):             | stereo RCA                                                                      |
| LINE 10 (front):              | stereo RCA/3.5 mm jack (1/8")                                                   |
| Minimum input voltage:        | 150 mV RMS                                                                      |
| PHONO 1.2:                    | stereo RCA                                                                      |
| Minimum input voltage:        | 3 mV RMS                                                                        |
| Outputs:                      |                                                                                 |
| MASTER 1.2:                   | stereo XLR/stereo RCA                                                           |
| Output voltage:               | 0.75 V/1.5 V RMS (switchable)                                                   |
| BOOTH:                        | stereo RCA/6.3 mm stereo jack                                                   |
| Output voltage:               | 0.75 V                                                                          |
| REC:                          | stereo RCA                                                                      |
| Output voltage:               | 0.75 V                                                                          |
| Headphones output:            | 3.5 mm/6.3 mm jack (1/8"/1/4") (min. 8 ohms)                                    |
| Tone control (DJ microphone): |                                                                                 |
| 1 x High:                     | -12 dB to +12 dB/ 10 kHz, $\pm 1$ dB                                            |
| 1 x Middle:                   | -12 dB to +12 dB/ 1 kHz, $\pm 1$ dB                                             |
| 1 x Low:                      | -12 dB to +12 dB/ 100 Hz, $\pm 1$ dB                                            |
| Talkover attenuation:         | -15 dB                                                                          |
| Tone control (MASTER):        |                                                                                 |
| 7-band equalizer:             | $\pm 15$ dB/ 60 Hz, 100 Hz, 400 Hz, 1 kHz,<br>2.4 kHz 6 kHz, 15 kHz, $\pm 1$ dB |
| S/N ratio:                    | >75 dB                                                                          |
| Distortion:                   | 0.03%                                                                           |
| Dimensions (WxHxD):           | 482 x 220 x 100 mm (19", 5 U)                                                   |