

OMNITRONIC PM-311 DJ mixer

3-channel DJ mixer

Art.n.: 10006876

GTIN: 4026397467154



L'articolo non è più disponibile.

Features :

- 3 input channels, switchable 2 x phono/line and 1 x aux/line
- Front aux input for portable music players (e.g. iPod)
- All input channels with gain control, 3-band equalizer and cue button
- DJ microphone input with talkover selector, level and 3-band equalizer
- Pre-fader listening (CUE) to the input channels and the master output via adjustable headphones output, with cue mix control
- Crossfader for crossfading between the phono/line channels
- 5-digit stereo LED level meter, switchable between master and PFL signal
- Additional recording output
- Operation via supplied power unit

Logistica

EAN / GTIN: 4026397467154

Peso : 2,20 kg

Lunghezza : 0.34 m

Larghezza : 0.24 m

Altezza : 0.12 m

Dati tecnici :

Alimentazione elettrica: 230 V AC, 50 Hz

Potenza totale installata: 4,00 W

Intervallo di frequenza: 20 - 20000 Hz

Misure:
Larghezza: 26 cm
Profondità: 17,2 cm
Altezza: 7,8 cm

Peso: 1,90 kg

via supplied power unit

Inputs:

Line/phono:	2 x stereo RCA
Line:	stereo RCA
Aux:	3.5 mm stereo jack
DJ microphone:	6.3 mm jack, unbal.

Outputs:

Master:	stereo RCA
Record:	stereo RCA
Headphones output:	6.3 mm stereo jack (min. 32 ohms)
S/N ratio:	>75 dB
Distortion:	<0.07 %