

OMNITRONIC EM-760A Entertainment mixer

6+1-channel mixer with 2 x 2-channel amplifier

Art.n.: 10007127

GTIN: 4026397219883



L'articolo non è più disponibile.

Descrizione :

The hybrid mixer!

This entertainment mixer boasts not only a compact design but also various connections and clever operating elements. What's so special about the EM-760A is the integrated amplifier and the option to combine the outputs. If you are satisfied with the output power and the range of the two integrated stereo amplifiers, just let each of them occupy one output. However, the output power can be increased by combining the two integrated amps to one output and connecting a further bigger amp to the free output. This is an option e.g. to achieve interesting sound effects for PA applications in larger rooms with different volumes.

Logistica

EAN / GTIN: 4026397219883

Peso : 17,50 kg

Lunghezza : 0.55 m

Larghezza : 0.53 m

Altezza : 0.22 m

Features :

- Amplifier with 4 x 150 W power/ 8 ohms
- 6 input channels with gain control, 3-way equalizer and super smooth dual-rail channel faders
- 1 separate microphone channel with level control, 2-way equalizer and talkover button
- Pre-fader listening (CUE) to the stereo input channels via adjustable headphone output
- Color illuminated rotary controls and rubber buttons
- 2 adjustable master outputs with 10-digit stereo LED level meter
- 1 adjustable booth output with mono/stereo selector switch
- 2 record outputs, independent of the master channels
- Inputs: 9 x line (stereo RCA), 3 x line/phono (stereo RCA), switchable; 6 x microphone (6.3 mm jack), 1 x microphone (XLR/6.3 mm jack) and headphones (6.3 mm jack)
- Outputs: 2 x master (optionally 3-pin XLR or stereo RCA), 1 x booth (stereo RCA) and 2 x record (stereo RCA)
- Speaker connection via lockable Speaker plugs or banana/screw combination
- Rack installation, 3 U

- Ideal for restaurants, bars, theme parks, hotels and all applications where microphones need to be mixed with music (e.g. karaoke)
- Montaggio su rack (19") 48,3 cm

Dati tecnici :

Alimentazione elettrica:	230 V AC, 50 Hz
Potenza totale installata:	900 W
Potenza in uscita:	Massimo 600 W (4 Ohm) 225 W RMS (4 Ohm) 150 W RMS (8 Ohm)
Intervallo di frequenza:	20 - 20000 Hz
Struttura della custodia:	Montaggio su rack (19") 48,3 cm
Misure:	Larghezza: 48,3 cm Profondità: 44 cm Altezza: 13,35 cm
Peso:	15,50 kg
Power output sine:	
Stereo 2 ohms:	4 x 320 W
Inputs:	
DJ microphone:	combined XLR/6.3 mm jack (1/4") (bal.)
Microphone 1-6:	6.3 mm jack (1/4") (bal.)
Minimum input voltage:	1 mV RMS
Line 1-9, Aux 1-3:	stereo RCA
Minimum input voltage:	150 mV RMS
Phono 1-3:	stereo RCA
Minimum input voltage:	3 mV RMS
Outputs:	
Master 1.2:	stereo RCA, stereo XLR
Output voltage:	0.75 V/1.5 V RMS (switchable)
Booth, Record:	stereo RCA
Output voltage:	0.75 V RMS
Speakers:	4 x Speaker, 4 x screw connectors
Headphones output:	6.3 mm stereo jack (min. 8 ohms)
Tone control (DJ microphone):	
1 x High:	-12 dB to +12 dB/ 10 kHz
1 x Low:	-12 dB to +12 dB/ 100 Hz
Tone control (channel 1-6):	
6 x High:	-12 dB to +12 dB/ 10 kHz
6 x Mid:	-12 dB to +12 dB/ 1 kHz
6 x Low:	-12 dB to +12 dB/ 100 Hz
Talkover attenuation:	-15 dB
S/N ratio:	>65 dB
Distortion:	0.02%
Dimensions (WxHxD):	483 x 440 x 135 mm (19", 3 U)