

OMNITRONIC DB-200 Decibel Level Meter

2-channel level display for audio signals with 2 x stereo RCA in and output

Art.n.: 10453014

GTIN: 4026397380682



Descrizione :

Take me to the next level!

Seeing things clearly is often very helpful - not only in the figurative sense. Let's think of a DJ's workplace. Surely you will find some small light sources, but in general it's not brightly illuminated. So sometimes it might get hard to read all instruments properly. The Omnitronic DB-200 can shed light on this darkness. The level meter is designed for displaying the level (two channels) of audio signals and it is equipped with three-color LEDs (40 LEDs per channel). Compared to normal mixers, it's much easier to read the audio signals as the LED scale is bigger and better arranged. You can even choose between dot or a bargraph display, just as you prefer. But there is one thing besides the benefit for the DJ which we shouldn't forget to mention. It's the effect of the LEDs. As eye-catcher at a DJ booth they really show up well.

Features :

- 3-color LED displays with 40 LEDs per channel
- Switchable display mode (dot display or bargraph display)
- Sensitivity control for each channel
- Display range: -27 dB to 0 dB
- Operation via supplied power unit
- Montaggio su rack (19") 48,3 cm 1 U

Dati tecnici :

Alimentazione elettrica: 230 V AC, 50 Hz

Potenza totale installata: 5 W

Logistica

EAN / GTIN: 4026397380682

Peso : 1,20 kg

Lunghezza : 0.57 m

Larghezza : 0.10 m

Altezza : 0.10 m

Allacciamento elettrico:	Alimentazione dell'energia elettrica tramite connettore cavo (M) versione da incasso cavo di alimentazione con alimentatore a spina (in dotazione)
Collegamenti:	Ingresso: 2 x RCA stereo Uscita: 2 x RCA stereo
Sensibilità di ingresso:	350 mV - 7 V
Campo di visualizzazione:	-27 db bis 0 db
Struttura della custodia:	Montaggio su rack (19") 48,3 cm 1 U
Misure:	Larghezza: 48,3 cm Profondità: 5,5 cm Altezza: 4,45 cm
Peso:	0,95 kg
	via supplied power unit
Input sensitivity:	approx. 350 mV to 7 V
Display range:	-27 dB - 0 dB (in 3 dB steps)
Audio inputs:	2 x stereo RCA
Audio outputs:	2 x stereo RCA

Contenuto della confezione:
