

## INTUSONIC HZE11 Zone Remote Control Panel

Commutatore di volume integrato, RS485, con telecomando IR

Art.n.: 12604189

GTIN: 5060502923301



### Descrizione :

The INTUGRID HZE11 provides a local control frontend for Intusonic's RS-485 enabled audio control systems, and by the nature of its user interface is the perfect complement for the HMA7x series of audio routers. It fits wall box sizes with minimal depth (86 mm) and hence can be mounted right where it is needed - in the room to be controlled. A standard CAT network cable is sufficient for connections; no additional power supply is required. Due to its daisy-chaining possibilities, more than one unit can be installed in a room, with the last operated one setting the system, and those settings being replicated on all HZE11 panels as well as the connected main unit. A local audio feed is possible via the provided 3.5mm jack for a stereo signal or alternatively via a 6.35mm jack for a mono microphone. For enhanced convenience, the HZE11 also sports an infrared remote control receiver and comes with a IRB44 remote control right out of the box.

### Features :

- Montaggio a incasso
- Multiple units can be linked
- Controllabile via Telecomando IR
- Schermo LCD
- Per maggiori informazioni su questo prodotto, consultare "Download" nella scheda tecnica

### Dati tecnici :

Alimentazione elettrica: 12V DC

Grado di protezione: IP20

### Logistica

EAN / GTIN: 5060502923301

Peso : 0,32 kg

Lunghezza : 0.11 m

Larghezza : 0.10 m

Altezza : 0.06 m

Attivazione:	Telecomando IR
Colore della custodia:	Nero
Tipo di display:	Schermo LCD
Collegamenti:	Ingresso: line via Jack da 3,5 mm (stereo) Ingresso: microfono via Presa jack (mono) da 6,3 mm versione da incasso RS 485 via RJ-45 (F) versione da incasso
Profondità di installazione:	30 mm
Struttura della custodia:	Montaggio a incasso
Misure:	Larghezza: 8,6 cm Profondità: 8,6 cm Altezza: 4,2 cm
Peso:	0,28 kg

### **Contenuto della confezione:**

1 x Dispositivo  
1 x telecomando  
1 x Pila  
6 x viti  
1 x Apertura  
1 x Manuale d'uso