


EUROLITE LED IP FL-30 COB RGB 120° RC

Outdoor spotlight (IP65) with 30 W COB LED (RGB) and IR remote control

Art.n.: 51914605

GTIN: 4026397455434



Features :

- Add highlights to your house and garden
- Ideal LED luminary for indoor or outdoor use
- Weather-proof housing (IP65)
- Mounting bracket for permanent installation included
- Extremely compact housing in an appealing design
- Equipped with 1 x 30 W COB RGB LED
- Beam reflection angle of 120°
- With LED driver
- Ready for connection via power cord with safety-plug
- IR-remote control with an operation range of approximately 7m included in delivery
- Automatic color change or manual program or color selection
- Built-in programs for color change and color fade
- Adjustable program speed and brightness
- Direct color selection for 15 preset colors + white
- 1 LED 30 W COB (chip-on-board) 3in1 R/G/B (miscela di colori omogenea)
- Il dispositivo è raffreddato tramite Raffreddamento a convezione passiva
- Controllabile via stand-alone; Telecomando IR
- With a beam angle of 120°
- Adatto per uso esterno IP65

Logistica

EAN / GTIN: 4026397455434

Peso : 1,80 kg

Lunghezza : 0.23 m

Larghezza : 0.20 m

Altezza : 0.17 m

Dati tecnici :

Alimentazione elettrica: 230 V AC, 50 Hz

Potenza totale installata: 36 W

Grado di protezione:	IP65
Classe di protezione:	CL I
Allacciamento elettrico:	Pavimento cavo di alimentazione con spina di protezione
Tipo di lampada:	Lampada a LED
Tipo di LED:	1 x 30 W COB (chip-on-board) 3in1 R/G/B (miscela di colori omogenea)
Raffreddamento:	Raffreddamento a convezione passiva
Attivazione:	Stand-alone; Telecomando IR
Angolazione del fascio di luce (1/2 picco):	120°
Colore della custodia:	Argento
Misure:	Larghezza: 22,6 cm Profondità: 12,5 cm Altezza: 19,5 cm
Peso:	1,68 kg
Pila:	1 x pila a bottone 3,0 V CR2025 litio-manganese montato
Prodotto speciale:	Non destinato all'illuminazione di ambienti domestici
Destinazione d'uso:	Illuminazione per effetti speciali

Contenuto della confezione:

1 x Proiettori
1 x telecomando
1 x Manuale d'uso