

EUROLITE FD-4 DMX dimmer panel

DMX lighting controller 4 channels

Art.n.: 70063801

GTIN: 4026397298932



L'articolo non è più disponibile.

Features :

- 4 channel faders with LED
- Fade time fader with LED for adjusting the step time
- Master fader with LED for adjusting the total output level
- Speed fader for adjusting the program-speed
- Flash button per channel and master-flash
- LED display of all modes
- 4 freely programmable programs with up to 84 steps each
- Controller comes with 4 pre-programmed chasers
- The programs and chasers can be called up individually or combined (CH1-2-3-4-PR-1-2-3-4)
- Dimmer: manual control of the channels via sliders
- Full On: all channels can be switched on together
- Blackout function
- Program speed adjustable via speed fader or tap sync button
- Sound-control via external signal or integrated microphone
- Sound to light via 6.3 mm jack
- Power supply via included power unit
- Only for professional use

Logistica

EAN / GTIN: 4026397298932

Peso : 1,72 kg

Lunghezza : 0.38 m

Larghezza : 0.24 m

Altezza : 0.15 m

Dati tecnici :

Alimentazione elettrica:	230 V AC, 50 Hz 9V DC 500 mA
Potenza totale installata:	1,00 W
Pila:	1 x 9.0 V E block (non in dotazione)

Misure:	Larghezza: 25,5 cm Profondità: 14,7 cm Altezza: 7 cm
	via 9-15 V DC, 300 mA power unit included in the delivery
	or 1 standard 9 V battery
Battery life:	approx. 3 hours
Number of control channels:	4
Integrated chasers:	4
Free programs:	4 x 84 scenes
Sound-control:	via built-in microphone or via audio-input
Audio-input:	Jack
Audio-sensitivity:	0.1-1 V
DMX512 output:	3-pin XLR connector
Dimensions (L x W x H):	255 x 147 x 70 mm
Weight:	1.5 kg