

OMNITRONIC PA 6-zone mono vol contr 5W sil

6-way PA volume controller with 24 V emergency priority relays

Art.n.: 80711328

GTIN: 4026397262360



Prezzo di listino: 42.72 €

incl. 19% IVA

Descrizione :

As you like it!

Whether in a shopping mall, at the airport, in a museum or in school, they are everywhere. Speaker systems operated with 100 V technology. They are used for announcements as well as background sounding. But what are you going to do if certain announcements are intended for designated rooms, sections or departments only? Or if the background sounding is not supposed to be at the same level everywhere? Right at this point we would like to introduce our zone controller, which divides the input signal to up to 6 zones, regulating each channel individually. However, 2 signals could - for example - also cover 3 zones each. A benefit compared to competing gadgets of the same category is the barrier on the back, which enables a really safe usage with the controller. After all there are mono versions as well as stereo versions. Both are available with different watt in black and silver.

Logistica

EAN / GTIN: 4026397262360

Peso : 3,20 kg

Lunghezza : 0.51 m

Larghezza : 0.25 m

Altezza : 0.15 m

Features :

- 6 audio transformers for 100 V line technique
- Attenuation in 10 steps
- 6 built-in 24 V emergency priority relays
- Aluminum front panel
- Connettore a vite
- Montaggio su rack (19") 48,3 cm 2 U

Dati tecnici :

Relè di ricezione obbligatorio: 24 V

Capacità di carico: Nominale: 6x 5W RMS

Intervallo di frequenza:	50 - 18000 Hz
Uscita zona:	6
Ingresso e uscita:	Mono
Struttura della custodia:	Montaggio su rack (19") 48,3 cm 2 U
Misure:	Larghezza: 48,3 cm Profondità: 23 cm Altezza: 8,9 cm
Peso:	2,60 kg